

CLAIMS

What is claimed is:

1. A digital gyrator, comprising:
a digital filter to emulate an inductance on a telephone
5 line serviced by said digital filter, said digital filter being initially settable
to a first cutoff frequency;
an oscillation checker module to detect an amplitude of
oscillation on said telephone line serviced by said digital filter, said
oscillation checker module adapted to reset said digital filter to a
10 second cutoff frequency lower than said first cutoff frequency as a
function of said detected oscillation level.
2. The digital gyrator according to claim 1, wherein:
said gyrator resets said digital filter to a third cutoff
15 frequency after a predetermined period of time after said digital gyrator
causes telephone equipment to enter an off-hook condition.
3. The digital gyrator according to claim 2, wherein:
said first cutoff frequency is significantly faster than said
20 third cutoff frequency.
4. The digital gyrator according to claim 2, wherein:
said predetermined period of time is at least one second.
- 25 5. The digital gyrator according to claim 1, wherein:
said first cutoff frequency relates to a desired
convergence rate when said telephone line is in a pre-charge state.
6. The digital gyrator according to claim 5, wherein:
30 said second cutoff frequency relates to a desired
convergence rate after said telephone line is in a steady state.

7. The digital gyrator according to claim 1, wherein:
said second cutoff frequency relates to a desired convergence rate after said telephone line is in a steady state.

5 8. The digital gyrator according to claim 1, further comprising:

 a digital load line correlation table to correlate values output from said digital filter into a desired voltage level.

10 9. The digital gyrator according to claim 8, further comprising:

 a codec to convert an output from said digital load line correlation table into a voltage signal for output to a DAA servicing said telephone line.

15 10. A method of regulating a signal on a telephone line, comprising:

 digitizing a signal received from said telephone line;

 filtering said digitized signal with a digital low pass filter

20 having a first cutoff frequency;

 detecting an amplitude of oscillation in said signal at said telephone line; and

 adjusting said digital low pass filter to have a second cutoff frequency lower than said first cutoff frequency to dampen said
25 detected oscillation if an amplitude of said oscillation indicates an unstable pre-charge state of said telephone line.

11. The method of regulating a signal on said telephone line according to claim 10, further comprising:

after a pre-charge period of said telephone line, adjusting said digital low pass filter to have a third cutoff frequency relating to a steady state of said telephone line.

12. The method of regulating a signal on said telephone line according to claim 10, wherein:

said first cutoff frequency is approximately 1 Hz.

13. The method of regulating a signal on said telephone line according to claim 12, wherein:

said second cutoff frequency is approximately 0.1 Hz.

14. The method of regulating a signal on said telephone line according to claim 10, wherein:

said second cutoff frequency is approximately 0.1 Hz.

15. Apparatus for regulating a signal on a telephone line, comprising:

means for digitizing a signal received from said telephone line;

means for filtering said digitized signal with a digital low pass filter having a first cutoff frequency;

means for detecting an amplitude of oscillation in said signal on said telephone line; and

means for adjusting said digital low pass filter to have a second cutoff frequency lower than said first cutoff frequency to dampen said detected oscillation if an amplitude of said oscillation indicates an unstable pre-charge state of said telephone line.

16. The apparatus for regulating a signal on said telephone line according to claim 15, further comprising:

means for adjusting said digital low pass filter after a pre-charge period of said telephone line, to have a third cutoff frequency
5 relating to a steady state of said telephone line.

17. The apparatus for regulating a signal on said telephone line according to claim 15, wherein:

said first cutoff frequency is approximately 1 Hz.
10

18. The apparatus for regulating a signal on said telephone line according to claim 17, wherein:

said second cutoff frequency is approximately 0.1 Hz.

19. The apparatus for regulating a signal on said telephone line according to claim 15, wherein:
15

said second cutoff frequency is approximately 0.1 Hz.